

Control Keypad JL-8260



Features

- ▶ Keypad with mechanical buttons of high resistance and integrate joystick
- ▶ LCD menu display
- ▶ Camera motion speed depending on the pressure on the joystick
- ▶ Allows to program up to 66 prefixed positions (Presets)
- ▶ 360° Automatically Scan function
- ▶ Allows to manage up to 255 different cameras
- ▶ RS-485 bus multi protocol, with RJ11 connector
- ▶ Configuration speed bus
- ▶ Power supply DC 9V (Power Supply Included)



TV
ACCESSORIES

Specifications

Model	JL-8260
Camera	255 Camera Address
Presets	66 Programmed Positions
Auto Tour	Pre-set Point Tour
Auto Scan	360° Horizontal Scanning
Protocols	Pelco-D, Pelco-P
RS-485 Connection	Regleta 4 contacts or RJ11 Connector
Communication Speed	Variable (1200, 2400, 4800, 9600 bps)
Power Supply	DC 9V
Power Consumption	3W
Working Conditions	Temperature : 0 ± 50°C Humidity : 10% - 90%
Dimension (mm)	314(L) x 209(W)
Weight	2kg

* All Specifications / colors are subject to change without notice. (V.01)

