

# Speed Dome Keyboard Controller JL-7260



## Features

- ▶ Keyboard controller with mechanical buttons of high resistance and integrate joystick
- ▶ LCD menu display
- ▶ Allows to program up to 64 prefixed positions (Presets)
- ▶ 360° Automatically Scan function
- ▶ Allows to manage up to 128 different cameras
- ▶ RS-485 bus multi protocol
- ▶ Power supply DC 9V (Power Supply Included)



TV  
 C  
 TV  
 ACCESSORIES

## Specifications

Model	JL-7260
Camera	255 Camera Address
Presets	64 Programmed Positions
Auto Tour	Pre-set Point Tour
Auto Scan	360° Horizontal Scanning
Protocols	Pelco-D, Pelco-P
Communication Speed	Variable (2400, 4800, 9600 bps)
Power Supply	DC 9V
Power Consumption	2W
Working Conditions	Temperature : 0° ± 60°C Humidity : 90% RH
Dimension (mm)	180(L) x 210(W) x 100(H)
Weight	approx. 1kg



\* All Specifications / colors are subject to change without notice. (V.02)