

# PA-250A

## 240W Power Amplifier 240W後級功率擴大機



### Features

- Adopt large external fins.
- Can be connected with multiple units to increase the power output.

### Specifications

Model	PA-250A
Power Supply	AC 230V 50Hz or DC 24V
Consumed Power	Rated Power 410W, Preparation : 35W
Input	0db, 50KΩ
Power Output	240W RMS
Loaded Impedance	100V.70V.0V , 16Ω.8Ω.4Ω.0Ω.
Frequency Response	20Hz ~ 20KHz ± 3dB (1KHz)
Distortion Rate	0.1% ± 5. (1KHz Output)
S/N Ratio	110dB ± 5. 20Hz ~ 20KHz
Protective Device	Automatic cut off protection function when overload
Temperature Range	0°C ~ +70°C
Main Color	White
Dimension	480mm(W) × 88mm(H) × 336mm(D)
Weight	12.9Kg

港澳總代理

#### CHECOL TECHNOLOGY LIMITED

TEL / FAX + (852) 2560 7011 / + (852) 2535 6388  
EMAIL mail@checol.com  
ADDRESS G/F, 57 King Yip Street, Kwun Tong, Kowloon, HK

