

# TA-120CD / TA-200CD

**120W/200W Synthetic Amplifier**  
 ( With CD set )  
 綜合擴大機 ( 附CD座 )



## Features

- This system has high-quality sound output as good as that of HI-FI stereo systems.
- The emergency alarm priority function.
- One original SONY CD player and one remote controller.
- The USB plug can be used to support the play of ordinary MP3.
- The CD player and the radio adopt module installation, so that they can be dismantled from the front panel directly in case of failure, without affecting the normal functions of the main machine.

### Specifications

	TA-120CD	TA-200CD
Model	TA-120CD	TA-200CD
Power Output	120W RMS / 200W	
Power Supply	AC 220V 50Hz, DC 24V	
Loaded Impedance	100V.70V.0V , 16Ω.8Ω.4Ω.0Ω.	
Input	MIC × 3, AUX × 3 (AUX1 and AUX2 can be switched to MIC)	
Frequency Response	20Hz ~ 15KHz ± 3dB (1KHz)	
Distortion Rate	0.1% ±5 (1KHz Output)	
Tone Control	Bass ± 10dB, Treble ± 10dB	
REC OUT	1KΩ 0dB	
CD Player	Manufactured by SONY Corp, DC 12V	
Main Color	Black	

港澳總代理

#### CHECOL TECHNOLOGY LIMITED

TEL / FAX + (852) 2560 7011 / + (852) 2535 6388  
 EMAIL mail@checol.com  
 ADDRESS G/F, 57 King Yip Street, Kwun Tong, Kowloon, HK

