

# TA-600 / TA-600A



## Amplifier for Teaching 教學擴音機

### Features

- The front and back ends are separated for the convenience of installation, maintenance and repair.
- Two microphones can be used at the same time.
- A switch can be used to switch from the outlet for microphone 2 into AUX input.

### Specifications

	TA-600	TA-600A
Model	TA-600	TA-600A
Power Supply	AC 230V 50Hz	
Frequency Response	50Hz ~ 20KHz	
Loudspeaker	8 Inches, 10 ~ 20W	
Loudspeaker output	92dB	
Input	2 Microphones or 1 Microphone and 1 AUX input	
Automatic power control	Auto Power On when microphone is inserted	
Input impedance	600Ω or 500KΩ	
Output Impedance	8Ω	
Distortion rate	0.3% at 1 KHz	
Max sound scope	102dB and above	
Material	ABS Resin	
Main Color	White	
Dimension	228mm(W) × 265mm(H) × 135mm(D)	
Weight	2.2 Kg	