# 64 Zone I/O BMS Indication Panel Controller




### Features

- High performance local alarm control panel designed for residential and commercial protections.
- It features of 64 zones sensor inputs / outputs, Alarm Reset, Mute Buzzer and Lamp Test Functions.
- Support varies of intrusion detectors, such as: Door / Window Contact, Glass Break Detector, Infrared Motion Detector, Ultrasonic Sensor, Panic Button and more.



### Dimensions



## Schematic Diagram



#### Specifications

Model	CHE-64ZAL910
Input	64 optically isolated inputs, Mute Buzzer Input,
	Reset Alarm Input, Lamp Test Input
Output	64 LED Outputs / Buzzer Output
Selectable Option	Selectable Input - NC. / NO.
Power Requirement	12VDC and 12VDC for optically isolated inputs
Operating Temperature	-10°C - 55°C
Dimension (mm)	285(W) x 187(H)
Weight	арргох. 425g

 $^{\star}$  All Specifications / colors are subject to change without notice. (V.01)





TEL / FAX +(852) 2560 7011 / +(852) 2535 6388 EMAIL mail@checol.com

EMAIL mail@checol.com

ADDRESS G/F, 57 King Yip Street, Kwun Tong, Kowloon, HK





